



# DECIMATOR-QUAD SETTINGS

In Quad Split mode, input 1 is displayed in the top left quadrant, 2 in the Top Right, 3 in the bottom left and 4 in the bottom right.

Use the rotary to select the menu and press the button to toggle the setting.

When the settings are changed the Power LED will change to Red and change back to Green when they are saved.

## **MENU = 0. Input Status (Buttons are disabled)**

LED	Description	LED Status			
		Off	Green	Red	Orange
1	Input 1 Format Detect	None	SD	HD	3G
2	Input 2 Format Detect	None	SD	HD	3G
3	Input 3 Format Detect	None	SD	HD	3G
4	Input 4 Format Detect	None	SD	HD	3G

## **MENU = 1. Output Format**

LED	Description	LED Status			
		Off	Green	Red	Orange
1	Output Format		PAL	NTSC	

LED 2, 3 and 4 are off.

NOTE: When SD-SDI is being passed through in full-screen the Output Format will match the input.

## **MENU = 2. Full Screen Enable**

LED	Description	LED Status			
		Off	Green	Red	Orange
1	Full Screen	Disabled	Enabled		

LED 2, 3 and 4 are off.

## **MENU = 3. Full Screen Input Select**

LED 1	LED 2	LED 3	LED 4	Input Selected
Green	Off	Off	Off	1
Off	Green	Off	Off	2
Off	Off	Green	Off	3
Off	Off	Off	Green	4

## **MENU = 4. Output Aspect and Type**

LED 1	Description
OFF	16:9 at 100% of screen size
GREEN	16:9 at 90% of screen size
RED	4:3 at 100% of screen size
ORANGE	4:3 at 90% of screen size

LED 2, 3 and 4 are off.

### MENU = 5. Aspect format for Input 1

LED	Description	LED Status		
		Off	Green	Red
1	SD Output Aspect Ratio	Input = Output	Letter/Pillar box	Centre Cut

LED 2, 3 and 4 are off.

### MENU = 6. Aspect format for Input 2

LED	Description	LED Status		
		Off	Green	Red
1	SD Output Aspect Ratio	Input = Output	Letter/Pillar box	Centre Cut

LED 2, 3 and 4 are off.

### MENU = 7. Aspect format for Input 3

LED	Description	LED Status		
		Off	Green	Red
1	SD Output Aspect Ratio	Input = Output	Letter/Pillar box	Centre Cut

LED 2, 3 and 4 are off.

### MENU = 8. Aspect format for Input 4

LED	Description	LED Status		
		Off	Green	Red
1	SD Output Aspect Ratio	Input = Output	Letter/Pillar box	Centre Cut

LED 2, 3 and 4 are off.

### MENU = 9. Border Enable

LED	Description	LED Status			
		Off	Green	Red	Orange
1	Border	Disabled	Enabled		

LED 2, 3 and 4 are off.

### MENU = A to C. RESERVED

### MENU = D. NTSC PEDESTAL

LED	Description	LED Status			
		Off	Green	Red	Orange
1	NTSC Pedestal	Disabled	Enabled		

LED 2, 3 and 4 are off.

### MENU = E.

Button 1 will reset all settings to their defaults.

### MENU = F.

LED	Description	LED Status			
		Off	Green	Red	Orange
1	Quad split mode output Reference	Free-run	Input 1		

LED 2, 3 and 4 are off.