



DECIMATOR

STATUS

| LED | Description | LED Status | | | |
|-----|-----------------|------------|-------|-----|--------|
| | | Off | Green | Red | Orange |
| 1 | Power | None | Good | | |
| 2 | Format Detected | None | SD | HD | 3G |

DIP SWITCHES

| SWITCH | | DOWN | UP (Default) |
|--------|-------------------------|-------------------|---|
| 1 | D.C. Output | PAL | NTSC |
| 2 | NTSC Pedestal | PEDESTAL for NTSC | |
| 3 | D.C. Output Aspect Type | CROP to 4:3 | Letterbox for 16:9 Full Screen for 4:3 |
| 4 | D.C. Output Aspect | 4:3 | 16:9 |

MOUNTING BRACKET

The Red Metal Mounting Bracket is included to assist you in mounting the DECIMATOR unit to the back of racks and monitors.

DIRECTIONS

Line up the holes on the Mounting Plate with the threaded slots found on the back, top and bottom, of the DECIMATOR unit. Attach the Mounting Plate as shown below.

